

If the Battery Is Low

1. To prevent an accidental short circuit, turn the ignition switch OFF (○).
2. Open the front hood (page 92).
3. Remove the battery box cover (page 158).
4. Using a fully charged 12-volt battery, connect the positive (+) side of the jumper cable to the charged battery, and connect the positive (+) side on the other end of the jumper cable to the positive (+) terminal of vehicle battery.
5. Connect the negative (–) side of the jumper cable to the charged battery, and connect the negative (–) side on the other end of the jumper cable to the front differential lock cable stay.
6. After starting the engine, remove the negative (–) sides of the jumper cable from the vehicle and the battery. Then remove the positive (+) sides of the jumper cable from the vehicle battery and the charged battery.
7. Install the battery box cover and close the front hood.
 - Do not let the positive (+) side of the jumper cable touch on the negative (–) terminal.
 - If the jumper cable is connected to the battery with the polarity reversed, the battery can explode or the electrical system will be seriously damaged.

