## **Starting Procedure**

This motorcycle has a fuel-injected with an automatic choke. Follow the procedure indicated below.

## Any Air Temperature

• With the throttle completely closed, press the start button.

The engine will not start if the throttle is fully open (because the electronic control module cuts off the fuel supply).

## Flooded Engine

If the engine fails to start after repeated attempts, it may be flooded.

- 1. Leave the engine stop switch set to (RUN).
- 2. Open throttle fully.
- 3. Press the start button for 5 seconds.
- Follow the normal starting procedure.
  If the engine starts with unstable idle, open the throttle slightly.

If the engine does not start, wait for 10 seconds, then follow steps 1-4 again.

## **Ignition Cut Off**

Your motorcycle is designed to automatically stop the engine and fuel pump if the motorcycle is over-turned (a banking sensor cuts off the ignition system). Before restarting the engine, you must turn the ignition switch to the OFF position and then back to ON.